



GRUPEL
energy everywhere

ENERGY ALWAYS AT HAND



PR

PORTABLERANGE

PORTABLE GENERATORS
GASOLINE | 2 - 15 kVA



PR

PORTABLE RANGE

	GR2500	GR3000	GR6500	GR12000
Main Features	Type	Single-Phase	Single-Phase	Single-Phase Three-Phase
	Continuous Power (PRP) (W)	2.000	2.800	6.300 11.000
	Starting Power (W)	2.200	3.000	6.900 12.000
	Frequency (Hz)	50	50	50
	AC Voltage (V)	230	230	230 / 400 230 / 400
	Automatic Voltage Regulator (AVR)	Yes / Inverter	Yes	Yes
	Fuel tank capacity (L)	4.5	15	25 40
	Fuel type	Unleaded petrol	Unleaded petrol	Unleaded petrol
	Engine type	4 stroke	4 stroke	4 stroke
	Starter system	Manual	Manual	Manual / Electric / Remote Electric / Remote
	Emissions certificate	STAGE V	STAGE V	STAGE V
	Safety for lack of oil	Yes	Yes	Yes
	Noise level (dBA)	68 @ 7m	96	96
	Autonomy at 100% load (h)	3.2	8.6	7 5,5
	L x W x H (mm)	500 x 285 x 455	660 x 600 x 500	760 x 700 x 650 1020 x 670 x 850
	Weight (kg)	22	52	104 183.5
Other Features	Sockets	1 schuko 16amp	2 schuko 16amp	1 Schuko 16amp + 1 single phase industrial 32amp + 1 3P+N+T 16amp 1 16A schuko + 1 32A/230V 3P CEE 1 16A/230V 3P CEE + 1 32A/400V 3P+N+PE
	Circuit Breaker	Yes	Yes	Yes
	Hour Counter	Digital	Digital	Digital
	Wheels and Handles	-	Yes	Yes
	Battery	No	No	Yes
	Voltmeter	Digital	Digital	Digital
	Frequency meter	Yes	Yes	Yes
	Auto Start	No	No	Yes (via Grapel ATS) Yes (via Grapel ATS)
	ATS (optional)	No	No	Yes (Single and Three-phase) Yes (Single and Three-phase)
	Remote Start	No	No	Yes
	DC Output	Yes (12vdc 8amp)	No	No
	USB	Yes (1.0A + 2.1A)	No	No
	Parallel operation	Yes	No	No



GR2500



INVERTER GENERATOR

Stable energy. Ideal for sensitive devices



LIGHT AND COMPACT

Weighing only 22kg, this generator is easy to carry and to handle



ALWAYS CONNECTED

It has got one socket, one DC output and two USB ports



DOUBLE THE ENERGY

It is possible to connect and use two GR2500 generators at the same time



GR3000



DIGITAL DISPLAY

Voltmeter, frequency meter and hour counter



FUEL TANK

The fuel tank has a capacity of 15L of gasoline



WHEELS AND FOLDABLE HANDLE

Easy to carry and to store



MANUAL START

The generator starts manually, by pulling the recoil starter



GR6500



DIGITAL DISPLAY

Voltmeter, frequency meter and hour counter



REMOTE START

It is possible to start the generator with a remote



WHEELS AND FOLDABLE HANDLE

Easy to carry and to store



AUTO START

It is possible to start the generator, automatically, via the GrupeL ATS



GR12000



MORE POWER

With 12 kW, the generator can support multiple devices simultaneously.



REDUCED EMISSIONS

Compliant with emission standards, including STAGE V.



REMOTE START

The generator can be started remotely.



COMPACT

Convenient dimensions for any type of environment.

PARALLEL KIT

With two GR2500 generators running in parallel it is possible to meet larger power needs. By connecting two sets of this model and using them simultaneously, you can power devices with more demanding loads or more equipment at the same time.

The power cables can be stored at the back of the unit when not in use.

Kit sold separately.





Grupel, S.A.

Parque Empresarial de Soza, Parcela-A, Lt-5

3840-342 Soza – Vagos – Portugal

T : (+351) 234 790 070 · grupel@grupel.eu · www.grupel.eu



Cofinanciado por:



UNIÃO EUROPEIA
Fundo Europeu
de Desenvolvimento Regional